

Yard-Vue™

Installation and Operating Instructions

Version 1.0



PLEASE READ THESE INSTRUCTIONS CAREFULLY BEFORE USING THIS
PRODUCT AND KEEP THIS MANUAL FOR FUTURE REFERENCE.

The state of art WAPP camera is capable of deliver high quality Digital High Definition (HD) video to your smart-mobile device(s), which would require higher internet bandwidth. Due to your local internet environment condition, your mobile device(s) may display black-screen or temporary disconnect to the WAPP camera.

- * Make sure the WAPP camera is operating with sufficient internet bandwidth, 1Mbps (upload/ download speed) is suggested.
- * For best performance, the smart-mobile device(s) need to be on Wi-Fi or 4G mobile network in order to receive maximum download speed.
- * When the internet transmission is low, your WAPP APP will automatically switch to Relay Mode:
 - By adjusting to “Better Streaming” in the system setting section may improve the WAPP APP performance.
- * Your internet bandwidth is limited. For best performance, try to avoid more than two users connecting to the WAPP camera simultaneously.
- * Make sure your smart-mobile device(s) is equipped with up-to-date technology, 1.5GHz dual core processor or equivalent is suggested.
- * If the signal strength of your Wi-Fi router is weak, there are several ways to improve transmission:
 - Change router/camera relative position to receive better signal.
 - Use wire Ethernet cable on the WAPP camera to establish connection between WAPP camera and your router.
 - Use Wi-Fi repeater/extender to maximize the service range of your Wi-Fi route.
 - Switch your router to 11b/11g mode in order to improve router service range.
 - Purchase extension cable or high gain antenna for your camera from the WAPP vendor.
- * Please make sure the memory card used is CLASS10 rated.

CONTENTS

INTRODUCTION	2
WIRELESS DEVICES OPERATING RANGE	2
IMPORTANT SAFETY PRECAUTIONS	2
KIT CONTENT	4
SAFETY AND INSTALLATION TIPS	5
NIGHT VISION	6
CAMERA INSTALLATION	6
CAMERA OVERVIEW	7
DOWNLOAD AND SETUP THE APP	8
LIVE VIEW / SNAPSHOT / RECORDING	11
VIEWING YOUR SNAPSHOTS	13
PLAYBACK YOUR VIDEOS	13
MAIN PAGE OVERVIEW	17
ADVANCED SETTING	22
ADMIN PASSWORD	23
EMAIL ALERT	23
TIME ZONE	24
DAYLIGHT SAVING	24
DEVICE SECURITY CODE	24
VIDEO SETTINGS	24
WI-FI SETTING	25
SENSITIVITY SETTING	26
EMAIL SETTING	26
SD CARD SETTING	27
OVERWRITE SD CARD	27
PROFILE SETTING	27
DEVICE INFORMATION	27
TROUBLE SHOOTING	28
PRODUCT SPECIFICATION	31
STORAGE MEDIA MANAGEMENT	32
APPENDIX: COMPATIBLE LIST	33

INTRODUCTION

PLEASE READ BEFORE YOU START

Always use discretion when installing CCTV equipment, especially in built-up areas. Ensure that any relevant local regulations are upheld to ensure the lawful installation of video recording/ surveillance; third party consent may be required.

WIRELESS DEVICES OPERATING RANGE

Ensure the Wi-Fi signal strength at the location(s) of the camera(s) provides the best possible reception from the Wi-Fi router. If necessary, to improve overall system performance, reduce the distance between the camera(s) and the Wi-Fi router. Alternatively, extend the range of the router with a Wi-Fi extender/repeater. Additionally, please note that certain devices, like wire-less phones or microwave ovens, can interfere with, or reduce Wi-Fi transmission.

IMPORTANT SAFETY PRECAUTIONS

Damage caused by non-compliance with this Operating Manual will void the warranty!
We will not assume any liability for damages to items or persons caused by improper handling or non-compliance with the safety notices & any warranty claim will be null and void in such cases.

1. Do not drop, puncture or disassemble the camera; otherwise the warranty will be voided.
2. Avoid submersion in water, and dry hands before handling (any electrical products).
3. Never pull on the power cables. Use the plug to unplug it from the wall outlet.
4. Do not expose the camera to high temperature or leave it in direct sunlight (pointing upwards at the sun). Doing so may damage the camera or cause camera temporary malfunction/loss of image.
5. Use the device with care. Avoid pressing hard on the camera body/lens.
6. For your own safety, avoid installing the camera or power off the camera when there is a storm or lightning.
7. Remove the power adapter during long periods between use.
8. Use only the accessories and power adapters supplied by the manufacturer.
9. To meet the regulations pertaining to parental responsibility, keep the devices out of the reach of infants.
10. Check power cables, do not get crushed or damaged by sharp edges whenever the devices are in operation.





FCC Compliance Statement: This device complies with Part 15 of the FCC rules. Operation is subjected to the following two conditions: (1) this

device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.



Products with CE Marking comply with EMC Directive (2014/30/EU); Low Voltage Directive (2014/35/ EU); RED (2014/53/EU); ROHS

Directive (2011/65/EU) issued by the Commission of the European Community. Compliance with these directives implies conformity to the following European Norms:

EMC: EN 301 489

LVD: EN 60950

Radio: EN 300 328


FCC/CE WARNING

This equipment has been tested and found to comply with limits for a Class B digital device, pursuant to Part 15 of the FCC rules and ETSI(EN) 300328. These limits are designed to provide reasonable protection against harmful interference in residential installations. This equipment generates, uses, and can radiate radio frequency energy, and if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does interference to radio or television equipment reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Move the equipment away from the receiver.
- Plug the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/television technician for additional suggestions.

You are cautioned that any change or modifications to the equipment not expressly approved by the party responsible for compliance could void your authority to operate such equipment.

DISPOSAL




If the camera system no longer functions or can no longer be repaired, it must be disposed of according to the valid statutory regulations. Disposal of spent batteries/accumulators:

You are required by law (Battery Ordinance) to return all spent batteries and accumulators. Disposing of spent batteries/accumulators with common household waste is prohibited! Batteries/accumulators that contain hazardous substances are marked with the symbols on the side. These symbols indicate that it is prohibited to dispose of these batteries/accumulators in the household waste. The abbreviations for the respective heavy metals are: Cd=cadmium, Hg=mercury, Pb=lead. You can return spent batteries and accumulators that can no longer be charged to the designated collection points in your community, outlets or wherever batteries or accumulators are sold. Following these instructions will allow you to fulfill the legal requirements and contribute to the protection of our environment!


System Contents

Wireless App Camera



x 1

Camera Stand




x 1

Camera Antenna




x 1

Power Adapter




x 1

Screw Pack




x 1

Quick Start Guide



x 1

USB to RJ-45 Connector
Cable (WAPP-GO1ISU-D)



x 1

Tools Required:

- Electric drill
- 5mm masonry drill bit
- 15mm masonry drill bit
- No. 2 Philips screwdriver

For best system performance:

- iOS: iPhone5 / iPad2 / Mini iPad with iOS 7.0 or above.
- Android: 1.5G dual core processor dual core processor with 1G Ram or above.
- Storage: Class 10 memory card (**8GB included**).
- Bandwidth: 1Mbps or above upload/download speed suggested.


SAFETY AND INSTALLATION TIPS

Do not attempt to open the units with the power adaptor plug connected to avoid any risk of personal injury.

When installing CCTV camera(s), always follow manufacturer's advice when using power tools, steps, ladders, etc. and wear suitable protective equipment (e.g. safety goggles) when drilling holes. Before drilling holes through walls, check for hidden electricity cables and water pipes. The use of cable/pipe detector is advisable.

It is also advisable to avoid exposing any cameras to extreme weather conditions (eg. under a gutter that may be prone to water leaks). When installing cameras, it is advisable to use cable conduit to protect any power extension cables from being exposed externally and to prevent/reduce the chances of the cables being tampered with. After drilling any holes through a wall etc, for the cable, ensure that the hole is sealed up around the cable using a sealant to prevent drafts/water ingress.


To prevent a fire or electrical shock hazard, do not attempt to open the housing while the unit is exposed to rain, water or wet conditions. There are no user serviceable parts inside. Refer servicing to qualified service personnel. Avoid pointing the camera(s) directly at the sun or any bushes, tree branches or moving objects that might unnecessarily cause the camera to record.




NIGHT VISION

The camera has built-in infrared LEDs to also allow you to view at night for 24-hour surveillance. The LEDs will automatically activate at night and the picture viewed will turn to black and white. The night viewing range is approx 5-10 meters (additional IR etc illumination may be required for larger areas).

CAMERA INSTALLATION




Secure the camera stand to a solid surface.




Loosen the thumb-screw.
Adjust to achieve the required viewing angle & then secure the thumb-screw.



Ceiling Mount



Wall Mount



CAMERA OVERVIEW



DOWNLOAD AND SETUP THE APP

The Wireless APP camera is designed to deliver live video footage directly to your smart phone or tablet device. Please follow these steps to download, setup and use the APP.


Download the App

Please download and install the "OMGuard HD" APP to your device.



BEFORE YOU START


- Before connecting the camera to power source, first connect the camera to your Wi-Fi router by using only the Ethernet cable provided.
- After the camera is connected to the Wi-Fi router, connect the camera to power source and wait until both RED and GREEN LED begin flashing. DO NOT begin the setup process until both LEDs become steady on (roughly 45 seconds).
- Please follow the steps in the following pages to complete the setup.




APP Setup


1. Make sure the mobile device you are using is connected to the same Wi-Fi router the camera is connected to.
2. Launch the "OMGuard HD" app.



3. Tap the  to add a new camera. Then click the SEARCH button for a quick setup. The APP will search available camera(s) connecting to the Wi-Fi router and display the camera information in the pop up list. Select the camera from the list and the APP will automatically add the camera's DID code to the DID column. Enter the **default password 123456**.



(iOS)



(Android)

Note:

After you have entered the default password, **123456**, the APP will remind you to change the default password (please 'note down' the new password for future reference).

4. Click SAVE to complete the camera settings. The system confirms the user identity and grants permission to user access.
5. You can refer to "ADD CAMERA" section for detail on adding additional camera(s).

In most cases, you can successfully add the camera according to the steps above. However, the camera will not find the network if Wi-Fi router turns off the SSID broadcasting function. Please enable the SSID broadcasting to complete the settings.

Note:

Most Wi-Fi routers broadcast the Service Set Identifier (SSID) by default. This is the name of your wireless network, and SSID broadcasting is how Wi-Fi-enabled devices find networks.

The camera will only accept SSID composed with English alphabet characters and Arabic numbers. Non-English and special characters (!@#\$%, etc.) will not be accepted.


APP INTRODUCTION

Main Page

The MAIN PAGE section offers user an overview for all registered camera(s), including camera status (connected/disconnected). User can quickly access the camera(s) in the list. When multiple cameras are registered, scroll down to locate the registered camera for access.



(iOS)



(Android)




The ADD CAMERA icon allows you to register additional camera(s) to the system. The system supports up to 3 concurrent user connections.




In the CAMERA SETTING section you will allow to (1) configure system setting, (2) unregister camera from the APP and (3) enter event list for recorded video file(s) playback. Tap the CAMERA SETTING icon to enter/exit CAMERA SETTING.

Tap the CAMERA SETTING icon. The following icons appear on the panel.



(iOS)



(Android)



Tap the ADVANCED SETTING icon to setup camera configuration. (Please refer to "Advanced Setting" for detail).



Tap the DELETE icon to remove the camera connection.



Tap the EVENT LIST icon to check or playback the recorded events. (Please refer to "Playback Your Video" for detail).



The INFORMATION icon allows you to enable PIN lock, push notification function and check the App information.

LIVE VIEW / SNAPSHOT / RECORDING



Tap to take snapshot image(s) of the video. The captured snapshots will be stored in your mobile device.



Tap to turn ON/OFF the volume.



Tap to Start/Stop recording. The recorded video file will be stored in the memory card of your camera.



Tap to return to the main page.

The APP allows users to have access to live video, take snapshot image(s) and record the live video.

When you launch the App on the smart phone or tablet, the image displaying on the main screen is the very last automatically captured snapshot from the live view of the previous established session. **Tap the image to enter live view mode.**

The controls and layout of the APP have been customized to meet the operating system requirements of the mobile device. The main page may vary, depending on your mobile device. By default, the live view is displayed in portrait mode. You can also turn the device sideways to switch to landscape mode for a larger view.

Note:

Once the recording is started by motion detection or manually, the APP will continue the recording for 1 minute; the user can not stop the recording during this period.

VIEWING YOUR SNAPSHOTS

For iOS

You snapshots will be named with the time stamp and saved into the Camera Roll location of your mobile device.

For Android


You snapshots will be named with the time stamp and saved into the **Photo Gallery > snapshot** folder on your mobile device.

PLAYBACK YOUR VIDEOS


The recorded video file(s) on your camera is automatically saved to the memory card inserted in your camera. You can remotely access the file(s) for playback via your mobile device.



Tap the CAMERA SETTING icon on the main page.




(iOS)



(Android)



Tap EVENT LIST icon and the Date-Time filter will appear. The user may define the period for system to display all available recorded file(s) for playback:




During the playback, tap the PAUSE icon to pause / resume the video. MUTE to deactivate/ activate the audio function and tap the BACK icon to return to the event list section. You may also review recorded video file(s) with your PC. For best performance, please use "Free Video Converter" from http://www.freemake.com/free_video_converter/, or Video LAN from <http://www.videolan.org/>.

The video is using FFmpeg codes and is H.264 compression method.

User's local network environment condition (example: '**low**' upload/download speed) may cause improper video playback (black screen). If this happens, please leave the playback mode and try again at later time (i.e. with 4G or 'high speed' Wi-Fi).


APP layout may vary depending on the display panel size of your mobile devices. Please refer to the release note from the APP Store/Google Play for more details.

To Download / Delete the video file(s) in the EVENT LIST section, please follow the steps below:



·DOWNLOAD


Long press the video clip to download the file onto your movbile device.



Note:

During the download process, the system will stop both the live view and recording functions. APP will automatically inform any user accessing the camera that the system is busy and the connection has been terminated.

This function helps the user to easily access the recorded file(s) from the memory card. It is strongly suggested to download the file(s) at your home Wi-Fi network (WLAN), meaning the mobile device(s) is connecting to the same Wi-Fi router as the camera. Minimum bandwidth requirement is 1Mbps (upload/download). Download process may be force stopped if the bandwidth becomes too slow and cannot continue.



Note:

For iOS system, please use "Oplayer Lite" APP for playback downloaded video files(s). You can find "Oplayer Lite" from App Store (free of charge)


Note:

For Android system, please use "MX Player" APP for playback downloaded video file(s). You can find "MX Player" from Google Play (free of charge).

If you are experiencing scattering video image, please switch the decoder function of the MX Player to "S/W Decoder".

·DELETE

First select the file(s) by tapping the file name, following by taping on the Trashcan icon to delete selected file(s) Multiple files can be selected for delete.



Check the video clip


Then tap the trash can icon

MAIN PAGE OVERVIEW

The MAIN PAGE section offers user an overview for all registered camera(s), including camera status (connected/disconnected). User can quickly access the camera(s) in the list. When multiple cameras are registered, scroll down to locate the registered camera for access.



(iOS)



(Android)


ADD CAMERA




The ADD CAMERA icon allows you to register additional camera(s) to the system. The system supports up to 3 concurrent user connections.

1. Connect the additional camera to the Wi-Fi router using the provided Ethernet cable. The Wi-Fi router must be the same as what your mobile device is connecting with.
2. Tap the ADD CAMERA icon. The System Information panel appears. Specify a name or use the default system name for your camera in the SYSTEM NAME field.
3. Enter the DID code that provided with your camera in the DID column.

4. Enter the default password **123456** in the Security Code column.

The image shows the 'System Information' screen on an iOS device. The status bar at the top shows 'No SIM', '7:38 PM', and '22%' battery. The screen contains the following fields: 'System Name' with the value 'Hd-000769', 'DID' with the value 'CGXX-000769-LDFMS', and 'Security Code' with four asterisks. Below these fields is a toggle switch for 'Enable E-Mail alert' which is currently turned off. At the bottom, there are three buttons: 'Search' (in blue), 'Cancel' (in blue), and 'Save' (in blue). Below these buttons is a link labeled 'Advanced'.

(iOS)

The image shows the 'System Information' screen on an Android device. The status bar at the top shows '11:52' and '99%' battery. The screen contains the following fields: 'System Name' with the value 'Hd-000769', 'DID' with the value 'CGXX-000769-LDFMS', and 'Security Code' with four asterisks. Below these fields is a checkbox for 'Enable Email Alert' which is currently unchecked. At the bottom, there are three buttons: 'Search', 'Cancel', and 'Save', all in grey. Below these buttons is a button labeled 'Advanced'.

(Android)

5. Click SAVE to complete the camera settings. The APP attempts to establish camera connection. Once the camera is successfully connected, the “Connected” status will be shown on the left upper corner.
6. Repeat step 2 to 5 to add more cameras.




In the CAMERA SETTING section you will allow to (1) configure system setting, (2) unregistered camera from the APP and (3) enter event list for recorded video file(s) playback. Tap the CAMERA SETTING icon to enter/exit CAMERA SETTING.

Tap the CAMERA SETTING icon. The following icons appear on the panel.



(iOS)



(Android)



Tap the ADVANCED SETTING icon to setup camera configuration. (Please refer to "Advanced Setting" for detail).



Tap the DELETE icon to remove the camera connection.




Tap the EVENT LIST icon to check or playback the recorded events. (Please refer to "Playback Your Video" for detail).



The INFORMATION icon allows you to enable PIN lock, push notification function and check the App information.

SETUP PIN LOCK



If you enable PIN Lock, the user will be asked to enter the PIN code when the APP is launched.

1. Enable the “Enable lock when starting” function, then enter your PIN code.
2. Confirm your PIN code again.

Note:

If you forgot your PIN code, please uninstall the APP and reinstall it on the mobile device.

NOTIFY (PUSH NOTIFICATION)

The WAPP camera supports a motion detection function. When any event is detected by the camera, a push notification will be received on the mobile devices recognized by the camera.


For iOS

If you want to enable/disable it, please follow the steps on your iOS mobile device:

1. Launch Settings from your Home screen.
2. Tap Notifications.
3. Scroll down to find “OMGuard HD” APP and tap on it.
4. Switch the toggle to ON/OFF in Notification Center.


Note:

It can take time for the changes to take effect in iOS, but normally within 2 hours.




Note:

The internet connection and wireless network interference may influence the performance of the push notification service.



(iOS)



(Android)

ADVANCED SETTING

This chapter explains the advanced settings for administrator. Administrator is the one who owns the administration password and has the full control to the WAPP camera. The administrator can access all WAPP functions and settings, while general users can receive the surveillance images for live view/screen capture/video recording and may not manage the camera settings.

Admin Password	The security code required to enter Advanced Setting for system setting management.
Email Alert	Enable / Disable receiving E-Mail alert (after system detecting motion) on your mobile device. Please make sure you have setup the E-Mail Setting correctly and have activated Motion Detection function.
Time Zone	Setup the appropriate time zone .
Daylight saving	Turn ON/OFF the daylight saving function.
Device Security Code	The password required for remote access.
Video Setting	Configure the video quality and local power frequency.
Wi-Fi Setting	Manage your Wi-Fi Network.
Sensitivity Setting	Setup the camera sensitivity for motion detection.
Email Setting	Setup your email account for E-mail alert .
SD Card Format	Format/Setup the SD card.
Profile Setting	Save the current camera settings and apply the settings to other cameras.
Device Information	Check the App and API Kernel version.

Note:

It may take more than one minute for some routers to update the registered devices. When you change the advanced settings and return to device list, please wait for a while, allowing your router to finish the camera registration.

ADMIN PASSWORD

The Admin Password is a specific security code for administrator to change the advanced settings.

The default admin password is 123456.

Please use this function to change the default admin password into your personal admin password. For the protection of your system configuration, every time you change the advanced settings, you need to enter the admin password. Please change the admin password periodically.

Note:

If you forgot your admin password, please long press the reset button on the camera DC jack for 5 seconds to restore the password into factory default value **123456** (please refer to the Camera Overview section). All settings will be restored to factory default. You will need to configure your camera from the start.

EMAIL ALERT

The camera supports a motion detection function, which is capable of detecting movements within the camera view, followed by a push notification and/or email alert to the user(s), the system can also begin recording to an internal micro-SD card.

When motion detection is enabled and system detects movement:

- System will begin recording.
- With Push Notification enabled, the system will send out a notification message to the user's mobile device.

With Email Alert enabled, to system will send out Email (Gmail accounts) to alert the user.

Function	Setting	Action (when movement is detected)
Email Alert	ON	Camera: Start video recording Email account: Email alert
Push Notification	ON	Camera: Start video recording Mobile Device: Text notificationMotion
Detection	OFF	Camera: Manual Recording Email account: No action Mobile Device: No action

Note:

By default, the system has been limited to send out the email alert every 1 minute to prevent overloading user's email account.

TIME ZONE

The drop-down list shows the world time zone. Select the time zone that will work the best for you. If your date/time is during the daylight saving time period, please check the Daylight Saving box to adjust the system time properly.

DAYLIGHT SAVING

Activate/Deactivate the daylight saving function.

DEVICE SECURITY CODE

The Device Security Code is a specific security code to access the camera.

The default password of the camera is **123456**. Please use this function to change the default password into your personal security code.

1. Type in the old password.
2. Type in the new password and confirm the new password again.
3. Tap OK to save the setting.

Note:

1. Change password in system information page accordingly.
2. If you forget the Device Security Code, please hold down the reset button (P.8) for 5 seconds to reset the system to factory default. All settings will be restored to factory default. You will need to configure your camera from the start.

VIDEO SETTINGS

This section allows you to configure the video quality and environment mode.

Video Quality

The Video Quality setting section allows you to adjust the quality of the video streaming. By selecting better video image it will allow you to view high resolution image. By selecting better streaming it will allow the video to display more smoothly (quality depend on local internet environment).

Only select better image when you have sufficient bandwidth and updated mobile device(s). Please refer to Page 4 for the system requirements.

Environment Mode

The Environment Mode settings allows you to select the power line frequency used at the location of WAPP camera. The power line frequency varies depending on geographic region. It may cause image flicker if the wrong frequency is selected. Please check with local authorities for proper setting.

There are two type video color tone, user can change the video color tone between warm-yellow(indoor) and cool-white (outdoor)

Low Light Enhancement

The Low Light Enhancement Mode is for improving the night view video image by providing 5 levels to select from (**5 = brightest**).

WI-FI SETTING

The Wi-Fi setting allows you to choose the wireless connection and setup the Wi-Fi environment.

When you tap the “Manage Wi-Fi network” button, the system automatically scans the nearby network and shows the available Wi-Fi routers in the drop-down list. Choose the appropriate Wi-Fi router and enter the Wi-Fi router password if necessary. Due to security concerns, it is suggested to use the WPA/WPA2/ WPA2-PSK protocol for Wi-Fi network.

Note:

1. When the Wi-Fi connection is completed and you unplug the Ethernet cable, the camera will reboot and it will take several minutes to establish the connection.
Please re-launch the APP when you see the green signal indicator light up.
2. The WAPP camera is designed to work with the legal Wi-Fi channels in your region.
Please refer to your Wi-Fi router manual to choose an appropriate channel for the WAPP camera.
3. If the camera fails to connect to the Wi-Fi router, please hold down reset button for 2 seconds to reset the system and repeat register process again.

SENSITIVITY SETTING

This defines the camera parameter for motion detection.

Detection Mode

PIR is hardware-based biomass detection.

SOFTWARE uses advance software analysis to trigger motion alarm.

In general, the performance of any PIR depends on the environment, especially the temperature. At low temperature the accuracy of PIR may suffer. If you are experiencing this, please switch to the built-in software motion detection to improve performance.

Motion Detection (available for Software Mode ONLY)

HIGH – Suitable for detecting smaller object(s) within 5 to 6 meters

LOW – Suitable for detecting larger object(s) within 3 to 5 meters

Note:

The HIGH/LOW setting for Motion Detection only takes effect when the user chooses SOFTWARE in detection Mode.

EMAIL SETTING

The email setting allows you to configure the email environment, email account and password. Gmail accounts are currently supported.

Click the “Use SSL” check box will transmit the data in encryption. This setting requires the Simple Mail Transfer Protocol (SMTP) configuration. Most ISPs use the SMTP method to transfer outbound mail via the internet. Only use the SMTP that supports SSL.

Gmail Setting (suggested)		
SMTP Server	smtp.gmail.com	Enter the gmail SMTP server
SMTP Port	465	Enter the SMTP port 465
Username	XXX@gmail.com	Enter your email address
Password	XXXXXXXXX	Enter the password for this gmail account
Email to	XXX@gmail.com	Enter the email address for the recipient who receives the email alert.

SD CARD SETTING

Formatting your memory card will ERASE all the data from it and you will not be able to restore the data. Please back up your video files BEFORE formatting the memory card.

Note:

The system is optimized for Class 10 memory cards. Memory cards with lower specification will decrease the recording and playback function efficiency.

During format process, all recording & viewing will stop until the format process completes.

OVERWRITE SD CARD

This function will overwrite the oldest files when the micro memory SD card is full. Turning on this function will enable the system to start overwriting the old files when the available memory card capacity is full. This ensures the most up to date video recordings are saved.

Note:

You should reformat the memory card from time to time to ensure the condition of the storage device. Your camera system will not work properly if the memory card becomes corrupted.

PROFILE SETTING

This function allows you to save the following customized settings of camera. This is useful if you want to apply the same settings to another WAPP camera quickly. You won't have to make all settings for each camera manually.

- Time zone
- Vido setting
- Sensitivity setting
- Email setting
- Overwrite Setting

DEVICE INFORMATION

This section shows the device information about the camera, including device version, total size and available size of the memory card.

TROUBLE SHOOTING

IF	SOLUTION
The APP can not find the camera	<ul style="list-style-type: none"> · Make sure your network supports the DHCP protocol. · Make sure the camera and your mobile device connect to the same Wi-Fi router for the first setting. · Make sure the Wi-Fi router is activated. · Make sure the camera is properly powered on. · Use the "ADD CAMERA" function to manually add the camera.
Wi-Fi router is not shown in the drop down list	<ul style="list-style-type: none"> · Make sure SSID broadcasting function is enabled in the Wi-Fi router. Consult your Wi-Fi router manufacturer for the settings if necessary. · Change the wireless security protocol of your Wi-Fi router into WPA/WPA2/WPA2-PSK. Due to security concerns, WEP protocol is not suggested for some Wi-Fi routers. <div> <p>Note: WPA/WPA2/WPA2-PSK encryption protocols are newer and more effective security standards for wireless networks than the older and less-secure WEP protocol.</p> </div>
No image appears	<ul style="list-style-type: none"> · Make sure the power adaptor is not damaged or defective and plugged into an electrical outlet with power. · Relocate the camera to obtain the best reception of wireless signals. · Make sure the camera is properly configured in App. · Make sure the mobile device is connected to 3G/4G/Wi-Fi properly.
Low wireless signal Poor image quality	<ul style="list-style-type: none"> · Wireless devices such as wireless home stereo system may reduce the signal strength. Leave as much space as possible between the camera/mobile device and these wireless devices. · Clean the camera lens using lens cleaning cloth. Spots or dust on the lens can also cause image quality problems.
Motion detection is not working or over-react	<ul style="list-style-type: none"> · Make sure the sensitivity setting is turned ON (please refer to the Sensitivity Setting section). · In motion detection mode, a moving object within the camera viewing angle is necessary to trigger the motion sensor for recording

The APP cannot record any video clips	<ul style="list-style-type: none"> · Make sure the SD card has been correctly inserted · Make sure the motion detection function has been enabled. (please refer to the Sensitivity Setting section). · Please format the SD card when it is used for the first time (please refer to the SD Card Format section) · Make sure you are using Class 10 rated memory card.
Email alert is not working	<ul style="list-style-type: none"> · Make sure the email alert function is enabled (please refer to the Email Alert section). · Gmail account is suggested for the email alert function. Make sure you have setup the system configuration as suggested in the Email Alert section. · Make sure the email address is has been correctly entered.
Bright white spots appear at night time	<ul style="list-style-type: none"> · The camera's infrared LEDs produce invisible light that reflects off surfaces such as glass. Install the camera on the other side of windows or place the lens flush against the surface to improve the night vision. It is suggested to install camera(s) under well-lit area. <div> <p>Note:</p> <p>Please check the environment rating (Ingress) of the camera(s) before installing outdoors.</p> </div>
Memory card error	<ul style="list-style-type: none"> · Make sure the memory card is correctly inserted and formatted. · Use the provided memory card within the package to ensure proper operation. · Make sure your are using Class 10 rated memory card. <div> <p>Note:</p> <p>Please backup the data before formatting. Format function will erase all the data on the memory card.</p> </div>
Wrong date and time are shown	<ul style="list-style-type: none"> · Wrong date and/or time will result in unexpected record schedule. Make sure you've selected the correct time zone (please refer to the Time Zone section). · Confirm the system date/time of the mobile device to ensure correct operation. · System will clock itself when connect to the internet. Make sure the system is connected properly to the internet. You may use your mobile device to access the system to see if remote view is functioning properly.

PRODUCTION SPECIFICATION

Networking Parameter	
Wireless Technology	IEEE 802.11 b/g/n
Network Connection	Ethernet (10/100 Base-T/Base -TX); Wi-Fi
Network Protocols	TCP/IP, UDP, SMTP, NTP, DHCP, ARP
Simultaneous Viewers	3 concurrent sessions
Security	WPA /WPA2/WPA2-PSK (TKIP, 128 bit AES)
Camera Parameter	
Image Sensor	Mega pixel CMOS
Antenna	3dBi Dipole
Housing	Weather resistance metal
Environment Rating (Ingress)	IP66
Light Source Environment	Indoor (50Hz); Indoor (60Hz)
Local Storage	Micro SD memory (not included in the package)
Viewing angle	H:90°, V: 45°
Lens	4.0mm
Min. Illumination	1~8 lux
Number of LEDs	6 IR LEDs with IR switcher
IR Distance	10 meters
Video Audio Parameter	
Image Compression	H.264
Image Resolution	HD 1920x1280
Recording Frame Rate	1080P@30 FPS
Supported Mobile Device	
iOS requirement	iPhone 5S / iPad Mini / iPad 2 with iOS 7.0 or above
Android requirement	Android 4.4X or above
Hardware requirement	1.5GHz dual core or above 1GB or above internal memory
General Parameter	
Power Requirements	100~240V switching power supply DC 5V 1.5A
Operating Temperature	-10°C~+50°C

STORAGE MEDIA MANAGEMENT

Micro SD Card Capacity (Class 10)	HD/Better Image
8G	400
32G	1,600
64G	3,200
128G	6,400

APPENDIX: COMPATIBLE LIST

WiFi Compatible Router List

Brand	Product Name
ASUS	RT-N53
BUFFALO	WIR-HP-C300NH2
BUFFALO	WZR-HP-G450
Cisco	ERT120
D-Link	DIR-816L
Huawei	WSR20
INTELBRAS	WRN300
NETGEAR	Wndr3700v4
NETGEAR	WGR614
Tenda	FS395
TP-link	TL-WR941N

Note:
Many other routers are also supported.

